



# MORTISE PRIVACY BOLT



No. 9163  
Traditional Turnpiece

The mortise privacy bolt is available for applications requiring privacy, such as bedrooms or bathrooms. This bolt is not meant for security purposes. In case of an emergency, the bolt can be retracted from the exterior side through the emergency release rose.

Two options of trim are available for the privacy bolt. The traditional turnpiece is meant to be paired with our traditional lever and knob sets. The beaded turnpiece complements our beaded lever and knob sets.

The auxiliary deadbolt is available for doors that are 1<sup>3</sup>/<sub>8</sub>" to 2<sup>1</sup>/<sub>4</sub>" thick.



No. 065  
Beaded Turnpiece

## 9163/238 or 9163/234

### MORTISE PRIVACY BOLT SET WITH TRADITIONAL TURNPIECE

- Available in 2<sup>3</sup>/<sub>8</sub>" (standard) and 2<sup>3</sup>/<sub>4</sub>" backsets
- Supplied with an outside rose for emergency release
- Inside rose and turnpiece: 1<sup>9</sup>/<sub>16</sub>"h x 1<sup>1</sup>/<sub>16</sub>"w x 1<sup>1</sup>/<sub>16</sub>"d
- Exterior emergency release rose: 1<sup>9</sup>/<sub>16</sub>"h x 1<sup>1</sup>/<sub>16</sub>"w x 3<sup>3</sup>/<sub>8</sub>"d
- Faceplate: 2<sup>1</sup>/<sub>4</sub>" x 1"; Strike: 2<sup>3</sup>/<sub>4</sub>" x 1<sup>1</sup>/<sub>8</sub>"
- Bolt: 9<sup>1</sup>/<sub>16</sub>" throw solid brass bolt

### Finishes

US3A

US3

US26

US10B

US14

US15

US5A

Also available  
in other finishes



No. 455  
Privacy Bolt

## 065/238 or 065/234

### MORTISE PRIVACY BOLT SET WITH BEADED TURNPIECE

- Available in 2<sup>3</sup>/<sub>8</sub>" (standard) and 2<sup>3</sup>/<sub>4</sub>" backsets
- Supplied with an outside rose for emergency release
- Inside rose and turnpiece: 2<sup>1</sup>/<sub>4</sub>"h x 1<sup>3</sup>/<sub>8</sub>"w x 1<sup>1</sup>/<sub>16</sub>"d
- Exterior emergency release rose: 2<sup>1</sup>/<sub>4</sub>"h x 1<sup>3</sup>/<sub>8</sub>"w x 3<sup>1</sup>/<sub>16</sub>"d
- Faceplate: 2<sup>1</sup>/<sub>4</sub>" x 1"; Strike: 2<sup>3</sup>/<sub>4</sub>" x 1<sup>1</sup>/<sub>8</sub>"
- Bolt: 9<sup>1</sup>/<sub>16</sub>" throw solid brass bolt